

## ТАБЛИЦА ВРЕМЕНИ РЕЗЕРВИРОВАНИЯ EATON 9E 6-20 кВА

Время автономной работы, мин	Нагрузка, %			
	25%	50%	75%	100%
<b>Модель</b>				
6Ki	42	19	11	8
6Ki+1EBM	162	75	47	33
6Ki+2EBM	252	107	70	50
6Ki+3EBM	383	163	104	74
6Ki+4EBM	523	222	140	100
10Ki	33	15	8	6
10Ki+1EBM	129	58	36	25
10Ki+2EBM	192	81	64	38
10Ki+3EBM	291	124	80	57
10Ki+4EBM	397	168	108	77
10KiXL+1EBM	79	33	20	12
10KiXL+2EBM	146	62	41	29
10KiXL+3EBM	240	102	67	48
10KiXL+4EBM	343	146	94	67
15Ki	38	16	9	6
15Ki+1EBM	88	37	26	18
15Ki+2EBM	170	79	49	34
15Ki+3EBM	208	88	58	41
15Ki+4EBM	274	116	76	54
20Ki	32	15	8	5
20Ki+1EBM	62	26	18	13
20Ki+2EBM	129	58	36	26
20Ki+3EBM	146	62	41	29
20Ki+4EBM	192	81	54	38
20KiXL+1EBM	26	11	8	6
20KiXL+2EBM	79	36	20	14
20KiXL+3EBM	102	43	29	21
20KiXL+4EBM	146	62	41	29